



T5 15W HE 4FT. DIR GL

MODEL

Model: 15T5HE/4F/xxx/GL/DIR

Where xxx means 824-965 which indicated CRI and color temperature



ELECTRONIC BALLAST COMPATIBILITY

Brand	Model	Type	Compatibility	
			(Ballasts are compatible with 120V & 277V unless otherwise noted)	
			1 Lamp	2 Lamps
GE - UltraMax	GE228MVPSH-A	PS	OK	OK
GE - UltraMax	GE228MVPS-MC	PS	OK	OK
Osram	QHE 2X28UNV PSN-SC	PS	OK	OK
Philips - Advance	ICN-2S28-N	PS	OK	OK
Philips - Advance	ICN-2S28-T	PS	OK	OK
Philips - Advance	IOP-2S28-95-SC-SD	PS	X	X
Philips - Advance	IOP-2S28-115-SC-SD	PS	X	X
Philips - Advance	IZT-128-D	PS / DIM	OK	OK
Philips - Advance	IZT-2S28-D	PS / DIM	OK	OK
Sylvania	QHE 2X28T5 / UNV DIM-CL	PS / DIM	X	X
Robertson	PSA228T5MV	PS	OK	OK
Robertson	REU128T5120	PS	Only 120V OK	X
Universal	B228PUNV-C	PS	OK	OK
Sola	E-725-U-228-R1-S	PS	OK	OK

*GREEN CREATIVE has provided this ballast compatibility chart for guidance when selecting a ballast and lamp combination. Lamps were tested for compatibility with the above listed Instant Start (IS) and Programmed Start (PS) ballasts. Ballasts that do not appear on the chart might still be compatible but have not been tested. All testing has been performed with a stable main supply. The quality of the local main, existing installation and wiring, as well as different manufacturer versions of the above ballasts may affect lamp performance. Since no assurance can be provided regarding these factors, it is a general recommendation to perform a test on-site prior to installing the LED lamps.

DIMMER COMPATIBILITY 0-10V

Brand	Series	Model	Load	Ballast		
				Philips		Sylvania
				IZT-128-D	IZT-2S28-D	QHE 2X28T5/UNV DIM-CL
Lutron	Diva	DVSTV	960W	OK	OK	X
Lutron	Diva	DVSCTV	1000W	OK	OK	X
Lutron	Diva	NTSTV-DV	960W	OK	OK	X
Legrand	Adorne	ADPD4FBL3P2	700W	OK	OK	X
Legrand	Harmony	H4FBL3P	1200W	OK	OK	X
Leviton	Illumatech	IP710-DLZ	1200W	OK	OK	X

OK = Fully Compatible X = Incompatible

*GREEN CREATIVE has provided this dimmer switch compatibility chart for guidance when selecting a dimmer and lamp combination. Our lamps were tested for compatibility with the above listed dimmers. Dimmers that do not appear on the chart might still be compatible but have not been tested. All testing has been performed with a stable main supply. The quality of the local main, existing installation and wiring, as well as different manufacturer versions of the above dimmers may affect dimming performance. Since no assurance can be provided regarding these factors, it is a general recommendation to perform a test on-site prior to installing the LED lamps.