



# DIRECT PLL

## MODEL

Model: 13PLL/xxx/GL/DIR  
13PLL/xxx/GL/DIR/R  
14.5PLL/xxx/GL/DIR

Where xxx means 824-965 which indicates CIR and color temperature



## ELECTRONIC BALLAST COMPATIBILITY

Model: 13PLL/xxx/GL/DIR 13PLL/xxx/GL/DIR/R

Series	Model	Type	Compatibility	
			(Ballasts are compatible with 120V & 277V unless otherwise noted)	
			1 Lamp	2 Lamps
Philips-Advance	ICN-1TTP40-SC	IS	Compatible	Not Compatible
Philips-Advance	ICN-2TTP40-SC	IS	Compatible	Compatible
Philips-Advance	ICF-2S42-M2-LD	PS	Compatible*	Compatible
Sylvania	QHE 1x40DL/UNV ISN-SC	IS	Compatible	Not Compatible
Sylvania	QTP 2X26/32/42CF/UNV DM	PS	Not Compatible	Compatible
Universal-Triad	C242UNVME	PS	Compatible	Compatible
Sylvania	QHE 2X40DL/UNV ISN-SC	IS	Compatible	Compatible
GE - UltraMax	GEC140MAX-A	IS	Compatible	Not Compatible
GE - UltraMax	GEC240MAX-A	IS	Compatible*	Compatible

\* Only 120V



# DIRECT PLL

## ELECTRONIC BALLAST COMPATIBILITY

Model: 14.5PLL/xxx/GL/DIR

Brand	Model	Type	Compatibility	
			(Ballasts are compatible with 120V & 277V unless otherwise noted)	
			1 Lamp	2 Lamps
Fulham	RHA-UNV-242-C	PS	Compatible	Compatible
Hatch	HC226PS/UV/D	PS	Compatible	Compatible
	HC242PS/UV/D	PS	Compatible	Compatible
Universal-Triad	C242UNVME	PS	Compatible	Compatible
	B254PUNV-D	PS	Compatible	Compatible
Howard	EP2/42CF/MV/2	PS	Compatible	Compatible
Philips-Advance	ICN-2S54-T	IS	Compatible	Compatible
	ICN-1TTP40-SC	IS	Compatible	Not Compatible
	ICN-2TTP40-SC	IS	Compatible	Compatible
	Izt-2S26-M5-BS	PS	Compatible	Compatible
	Izt-2TTS40-SC	PS	Not Compatible	Compatible
	Izt-2T42-M5-LD	PS	Compatible	Compatible
GE	GEC140MAX-A	IS	Compatible	Not Compatible
	GEC240MAX-A	IS	Compatible	Compatible
Sylvania	QHE 1x40DL/UNV ISN-SC	IS	Compatible**	Not Compatible
	QHE 2x40DL/UNV ISN-SC	IS	Compatible	Compatible

\*\* Only 277V

GREEN CREATIVE has provided this ballast compatibility chart for guidance when selecting a ballast and lamp combination. Lamps were tested for compatibility with the above listed Instant Start (IS) and Programmed Start (PS) ballasts. Ballasts that do not appear on the chart might still be compatible but have not been tested. All testing has been performed with a stable main supply. The quality of the local main, existing installation and wiring, as well as different manufacturer versions of the above ballasts may affect lamp performance. Since no assurance can be provided regarding these factors, it is a general recommendation to perform a test on-site prior to installing the LED lamps. Lamps that do not appear on the chart might still be compatible but have not been tested. All testing has been performed with a stable main supply. The quality of the local main, existing installation and wiring, as well as different manufacturer versions of the above ballasts may affect lamp performance. Since no assurance can be provided regarding these factors, it is a general recommendation to perform a test on-site prior to installing the LED lamps.